

## ENERPULSE PBM For Battery Charger



### Key Features:

- 230VAC Single Phase input supply, 50/60Hz Frequency
- 230/400VAC Three Phase input supply, 50/60Hz Frequency
- Pulse profile charging
- Electronic controller with PBM250 with 8mm LED
- 800 cycles charge memory
- Possibility of external accessories like AIR PUMP, top up and remote signal
- The charging parameters are programmable via a SW PBM service using a USB communication port
- Special VAC available on request

### Technical Specifications

ENERPULSE	Ah Battery	
Model	10 ÷ 12 h	Mains
24V/80A	480÷560	230V
24V/90A	540÷630	230V

24V/70A	420÷490	400V
24V/80A	480÷560	400V
24V/100A	600÷700	400V
24V/120A	720÷840	400V
24V/140A	840÷980	400V
24V/160A	960÷1120	400V
24V/180A	1080÷1260	400V
24V/200A	1200÷1400	400V

36V/50A	300÷350	230V
---------	---------	------

ENERPULSE	Ah Battery	
Model	7÷8 h	Mains
24V/80A	400÷440	230V
24V/90A	450÷495	230V

24V/70A	350÷385	400V
24V/80A	400÷440	400V
24V/100A	500÷550	400V
24V/120A	600÷660	400V
24V/140A	700÷770	400V
24V/160A	800÷880	400V
24V/180A	900÷990	400V
24V/200A	1000÷1100	400V

36V/50A	250÷275	230V
---------	---------	------

36V/60A	360÷420	230V
---------	---------	------

36V/50A	300÷350	400V
36V/60A	360÷420	400V
36V/80A	480÷560	400V
36A/100A	600÷700	400V
36V/120A	720÷840	400V
36V/140A	840÷980	400V
36V/160A	960÷1120	400V
36V/180A	1080÷1260	400V

48V/45A	270÷315	230V
---------	---------	------

48V/60A	360÷420	400V
48V/80A	480÷560	400V
48V/100A	600÷700	400V
48V/120A	720÷840	400V
48V/140A	840÷980	400V
48V/160A	960÷1120	400V
48V/180A	1080÷1260	400V
48V/200A	1200÷1400	400V

80V/40A	240÷280	400V
80V/60A	360÷420	400V
80V/80A	480÷560	400V
80V/100A	600÷700	400V
80V/120A	720÷840	400V
80V/140A	840÷980	400V
80V/160A	960÷1120	400V
80V/180A	1080÷1260	400V

36V/60A	300÷330	230V
---------	---------	------

36V/200A	250÷275	400V
36A/220A	300÷330	400V
36V/80A	400÷440	400V
36A/100A	500÷550	400V
36V/120A	600÷660	400V
36V/140A	700÷770	400V
36V/160A	800÷880	400V
36V/180A	900÷990	400V

48V/45A	255÷248	230V
---------	---------	------

48V/60A	300÷330	400V
48V/80A	400÷440	400V
48V/100A	500÷550	400V
48V/120A	600÷660	400V
48V/140A	700÷770	400V
48V/160A	800÷880	400V
48V/180A	900÷990	400V
48V/200A	1000÷1100	400V

80V/40A	200÷220	400V
80V/60A	300÷330	400V
80V/80A	400÷440	400V
80V/100A	500÷550	400V
80V/120A	600÷660	400V
80V/140A	700÷770	400V
80V/160A	800÷880	400V
80V/180A	900÷990	400V

TAKE BACK THE POWER!



[www.fastchargeaust.com.au](http://www.fastchargeaust.com.au)

P: 1800 084 099

[service@fastchargeaust.com.au](mailto:service@fastchargeaust.com.au)